

Menu Structure of Monitor *BenQ BL3201PT*

Main Menu

Display	PIP / PBP	Mode	PIP (Picture In Picture) PBP (Picture By Picture) • OFF
		PIP / PBP Source	• DVI HDMI1 HDMI2 DisplayPort
		SWAP	
		PIP Size	Large • Medium Small
		PIP Position	• Top Right Top Left Bottom Right Bottom Left
	Auto Pivot	• ON / OFF	
	Input	DVI HDMI1 HDMI2 DisplayPort Mini DisplayPort	

Picture	Brightness	0..100 (100)	(not if DynamicContrast or Eye Protect)
	Contrast	0..100 (50)	(not if DynamicContrast)
	Sharpness	1..10 (5)	
	Gamma	1 (1.0) 2 • 3 (2.2) 4 5 (2.7)	(only in picture mode Standard)
	Color Temperature	• Normal Bluish Reddish User Define	(only in picture mode Standard & User) (only in picture mode User)
			R 0..100 (red, 100) G 0..100 (green, 100) B 0..100 (blue, 100)
	Hue	0..100 (50)	
	Saturation	0..100 (50)	
	Reset Color	YES / • NO	
	AMA	OFF • High Premium	Advanced Motion Acceleration (pixel overdrive)

Picture Advanced	Picture Mode	sRGB		
		CAD / CAM		
		Animation	0..10 (1)	
		Presentation		
		• Standard		
		Low Blue Light	• Multimedia -30 %	
			Web Surfing -50 %	
			Office -60 %	
			Reading -70 %	
		Movie		
		Photo		
		Eco		
		M-book	(McBook adaption)	
		User		
		Senseye Demo	ON / • OFF	(only in some picture modes)
		DynamicContrast	• 0, 1, .. 5	(only in picture mode Movie or Photo)
		Overscan	ON / • OFF	(only if HDMI input)
	Display Mode	• Full		
		Aspect		
		1 : 1		
		19s"		
		22"(16 : 10)		
		23"		
		24"		
		24"(16 : 10)		
		27"		
		27"(16 : 10)		
		30"		
	Smart Scaling	?		
	HDMI RGB PC Range	• RGB(0 ~255)	(only if HDMI input)	
		RGB(16 ~235)		

Audio	Volume	0..100 (30)	
	Mute	ON / • OFF	
	Audio Select	PC Audio	
		• Auto Detect	

System	OSD Settings	Language	English, ...
		Display Time	5 sec. / 10 sec. / ● 15 sec. / ... / 30 sec.
		OSD Lock	„OSD locked! Hold any key 10 sec. to unlock.
Custom key 1		Picture Mode	key 1
Custom key 2		CAD / CAM	
Custom key 3		Animation	
		Low Blue Light	
		Display Mode	
		Brightness	
		Contrast	
		Volume	key 3
		Mute	
		Input	key 2
		Eye Protect	
		Eye Protect Meter	
		ECO Sensor	
		ECO Sensor Meter	
		Smart Reminder	
DDC / CI		● ON / OFF	
DP Auto Switch		● ON / OFF	
HDMI Auto Switch		ON / ● OFF	
Auto Power off		● OFF	
		10 min.	
		20 min.	
		30 min.	
Resolution Notice		● ON / OFF	
Information		Input	...
		Current Resolution	3 8 4 0 x 2 1 6 0 @ 60
		Optimum Resolution	3 8 4 0 x 2 1 6 0 @ 60
DisplayPort		1.1 / ● 1.2	
Controller key 1		sRGB	key 1
Controller key 2		CAD / CAM	key 2
Controller key 3		Animation	
		Presentation	
		Standard	
		Low Blue Light	key 3
		Movie	
		Photo	
		Eco	
		M-book	
		User	
		Brightness	
		Volume	
		Input	
Reset All		YES / ● NO	Reset All Settings ?

ERGONOMICS	Eye Protect	ON / ● OFF	(only in picture mode Standard, automatic brightness)
	Eye Protect Meter	ON / ● OFF	
	Smart Reminder	ON / ● OFF	
	Time Interval (min.)	● 20 min. 20 min. 40 min. 60 min. 80 min. 100 min.	
	Duration (sec.)	● 5 sec. 10 sec. 15 sec. 20 sec. 25 sec.	

ECO	ECO Sensor	ON / ● OFF
	ECO Sensor Meter	ON / ● OFF
	Sensor Range	Near / Middle / ● Far

Picture Modes of Monitor BenQ BL3201PT

Picture Mode	sRGB	CAD / CAM	Animation	Prese- ntation	Standard	Low Blue Light	Movie	Photo	Eco	M-book	User
<i>Brightness</i>	●	●	●	●	(●)	●	(●)	(●)	-	●	●
<i>Contrast</i>	●	●	-	●	●	●	(●)	(●)	-	●	●
<i>Sharpness</i>	●	●	●	●	●	●	●	●	●	●	●
<i>Gamma</i>	-	-	-	-	●	-	-	-	-	-	●
<i>Color Temperature</i>	-	-	-	-	●	-	-	-	-	-	●+
<i>Hue</i>	-	-	-	-	-	-	-	-	-	-	●
<i>Saturation</i>	-	-	-	-	-	-	-	-	-	-	●
<i>SensEye Demo</i>	-	●	●	-	-	-	●	●	-	●	-
<i>DynamicContrast</i>	-	-	-	-	-	-	●	●	-	-	-
<i>Eye Protect</i>	-	-	-	-	●	-	-	-	-	-	-

Controller Key Assignment

	<i>default: picture modes</i>	<i>example</i>
Controller key 1	sRGB	User
Controller key 2	CAD / CAM	Standard
Controller key 3	Low Blue Light	Brightness

Panel Key Assignment

	<i>default</i>	<i>example</i>
Custom key 1	Picture Mode	Display Mode
Custom key 2	Input	Picture Mode
Custom key 3	Volume	Input
key 4	Main menu	
key 5	Exit	